

Technical Bulletin

ISS45 TeamPoS S-Class Cash Drawer Setup with Epson 6000 and OPOS

ISS45-TECH-06:36
December 19, 2006

The Cash Drawer fired by an Epson 6000, 6000II or 6000III with the TeamPoS 2000 S-Class and OPOS should be set up as follows using the Epson OPOS utility:

- 1) Highlight CashDrawer and click on the Add New Device ICON
- 2) On the dropdown Device Name - select Standard (do not select Multi_A or Multi_B)
- 3) On the dropdown Select detailed model – select Standard
- 4) In the Add New LDN box for the name – add TM-H6000II (The name just needs to match what you put in the WinPOS.ini later)
- 5) Select Next to go to the next screen
- 6) For COM Port Settings select COM3
- 7) Click on Device Specific Settings
- 8) Change the Open Status Phase to High and leave the Connector Pin at 2
- 9) Run the CheckHealth Interactive test. Clicking Start, should pop open the drawer connected to the printer if the above is correctly configured.
- 10) Exit the OPOS setup and then go to the WinPOS.ini file and put in the following:
 OposDrawer=Yes
 DefaultDrawerName=TM-H6000II
- 11) In the POST config screen set the following
 Drawer in use
 Connected t printer

The NegativeDrawer line is *not* needed in the WinPOS for the Epson printer