

## Technical Bulletin

### ScanMaster Registry Change for Datalogic 8300/8400 with USB / OPOS

SM-TECH-09:15  
August 4, 2009

Regarding the Magellan 8300/8400 Scanner/Scale with ScanMaster on USB with the Datalogic 1.12 OPOS Driver, the following change must be made in the registry.

[HKEY\_LOCAL\_MACHINE\SOFTWARE\OLEforRetail\ServiceOPOS\SCANNER\TableScanner]

The default setting installed with Datalogic OPOS 1.12 is: USBMonitor=1

This setting needs to change to "0": USBMonitor=0

You can obtain a revised registry on the StoreNext Web site from the [Drivers Page](#). Select "Datalogic Drivers FTP" and "SM8400" and download the file called "8400 TableScanner.reg".

When installing, click and select Yes when prompted to add to registry.

Press OK when told import was successful.