

Technical Bulletin

ISS45 V7 AutoLock Operation

ISS45-TECH-05:23

May 10, 2005

Here is how the Auto Lock feature needs to be set up so that it works correctly. Listed below is how the V7 (any level of ISS45) E-OF-DAY.BAT should look for expected operation. The two original lines are remarked out and a new line added that reads either:

- Single period = `pcmcprep /e /from=1 /upto=9999 /curr /lock`
- Dual period = `pcmcprep /e /from=1 /upto=9999 /prev /lock`

Here is an example of how the E-OF-DAY.BAT file will look after this change for single period with Auto Lock feature:

```
:AUTOLOAN
:*****
printeod Performing cashier locking report to file >> log\e-of-day.log
REM PCMCREP /e /from=1 /upto=9999
REM PCMZCASH /e /lock /from=1 /upto=9999
pcmcprep /e /from=1 /upto=9999 /curr /lock
text2fil #e-of-day.bat #21 #CASHLOCK #8
:CASHLOCK
```

Here is an example of how the E-OF-DAY.BAT file will look after this change for dual period with Auto Lock feature:

```
:AUTOLOAN
:*****
printeod Performing cashier locking report to file >> log\e-of-day.log
REM PCMCREP /e /from=1 /upto=9999
REM PCMZCASH /e /lock /from=1 /upto=9999
pcmcprep /e /from=1 /upto=9999 /prev /lock
text2fil #e-of-day.bat #21 #CASHLOCK #8
:CASHLOCK
:*****
```

To Your Success,


Speros Voss
Technical Support

This document and information are supplied to StoreNext Retail Technologies personnel and third parties to assist them in doing business with StoreNext. They are not to be used or distributed for any other purpose.

StoreNext Retail Technologies LLC endeavors to ensure that the information in this document is correct and fairly stated, but does not accept liability for any error or omission.